NG4-VDML1MSB211C2K



NG4access® Module VAM, DWDM, 16 channels, 200 GHz channel spacing, starting channel 21, 1 circuit, Mux, LC/APC, left, 2 test ports

- VAMs help enhance optical transport systems by providing flexible, easy to incorporate optical components into the network
- VAMs increase fiber capacity and help troubleshooting or distributing signals to multiple subscribers
- *Product complies with the Build America, Buy America Act (BABAA) requirements of the Infrastructure Investment and Jobs Act of 2021 (Pub. L. 117- 58, §§ 70901-70953), or is the subject of a waiver approved by the Secretary of Commerce or designee. Compliance requirements and waiver applicability vary based on government funding program. Check the laws and regulations for your specific program.

Product Classification

Regional Availability Latin America | North America

PortfolioCommScope®Product TypeDWDM moduleProduct BrandNG4access®Product SeriesFACT | NG4

Government Funding Build America Buy America (BABA) compliant*

General Specifications

Device Type Plug-and-play module

Functionality Multiplexing

Application For use with NG4 access frames

Circuits, quantity 1

Distribution Type 16-channel DWDM

Interface, frontLC/APCInterface, InputLC/APCInterface, OutputLC/APC

Multiplexers, quantity 1

Port Type, optional Test port

Tray Orientation Left orientation

Dimensions

COMMSCOPE®

NG4-VDML1MSB211C2K

 Height
 13.21 mm | 0.52 in

 Width
 159.77 mm | 6.29 in

 Depth
 130.3 mm | 5.13 in

Optical Specifications

Channel Spacing 200 GHz

Starting Channel Number 21

Packaging and Weights

Packaging quantity

Regulatory Compliance/Certifications

Agency Classification

CHINA-ROHS Below maximum concentration value

REACH-SVHC Compliant as per SVHC revision on www.commscope.com/ProductCompliance

ROHS Compliant UK-ROHS Compliant

