

# 6-port sector antenna, 2x 694–960 and 4x 1695–2690 MHz, 65° HPBW, 3x RET with tilt scales

- All Internal RET actuators are connected in "Cascaded SRET" configuration
- Supports re-configurable antenna sharing capability enabling control of the internal RET system using up to two separate RET compatible OEM radios

#### OBSOLETE

#### This product was discontinued on: March 31, 2021

#### Replaced By:

RVV-65D-R3

6-port sector antenna, 2 x 694-960 and 4x 1695–2690 MHz, 65° HPBW, 3x RET

### General Specifications

Antenna Type	Sector
Band	Multiband
Grounding Type	RF connector inner conductor and body grounded to reflector and mounting bracket
Performance Note	Outdoor usage   Wind loading figures are validated by wind tunnel measurements described in white paper WP-112534-EN
Radome Material	Fiberglass, UV resistant
Radiator Material	Low loss circuit board
Reflector Material	Aluminum
RF Connector Interface	7-16 DIN Female
RF Connector Location	Bottom
RF Connector Quantity, high band	4
RF Connector Quantity, low band	2
RF Connector Quantity, total	6

#### Remote Electrical Tilt (RET) Information

RET Hardware	CommRET v2		
RET Interface	8-pin DIN Female   8-pin DIN Male		
RET Interface, quantity	2 female   2 male		
Input Voltage	10-30 Vdc		

Page 1 of 4

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: September 9, 2024



Internal RET	High band (2)   Low band (1)				
Power Consumption, idle state, maximum	1 W				
Power Consumption, normal conditions, maximum	8 W				
Protocol	3GPP/AISG 2.0 (Single RET)				
Dimensions					
Width	350 mm   13.78 in				
Depth	208 mm   8.189 in				
Length	2688 mm   105.827 in				
Net Weight, without mounting kit	31.3 kg   69.005 lb				

### Array Layout



Array	Freq (MHz)	Conns	RET (SRET)	AISG RET UID
R1	694-960	1-2	1	CPxxxxxxxxxxxxR1
Y1	1695-2690	3-4	2	CPxxxxxxxxxxxxXXXXXXXXXY1
Y2	1695-2690	5-6	3	CPxxxxxxxxxxxxXXXXXY2

Left Right Bottom (Sizes of colored boxes are not true depictions of array sizes)

### Port Configuration

Page 2 of 4

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: September 9, 2024





### **Electrical Specifications**

Impedance	50 ohm			
Operating Frequency Band	1695 – 2690 MHz   694 – 960 MHz			
Polarization	±45°			
Total Input Power, maximum	900 W @ 50 °C			

### **Electrical Specifications**

Frequency Band, MHz	694-790	790-890	880-960	1695-1920	1920-2180	2300-2500	2490-2690
Gain, dBi	16.6	17	17.2	18.4	19	19.5	19.2
Beamwidth, Horizontal, degrees	67	65	63	62	61	61	61
Beamwidth, Vertical, degrees	8.2	7.4	6.8	5.4	4.9	4.3	4.1
Beam Tilt, degrees	0-10	0-10	0-10	2-12	2-12	2-12	2-12
USLS (First Lobe), dB	18	21	18	17	17	20	21
Front-to-Back Ratio at 180°, dB	30	32	33	34	38	37	35
Isolation, Cross Polarization, dB	28	28	28	28	28	28	28
Isolation, Inter-band, dB	30	30	30	30	30	30	30
VSWR   Return loss, dB	1.5   14.0	1.5 14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0

Page 3 of 4

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: September 9, 2024

**COMMSCOPE**°

PIM, 3rd Order, 2 x 20 W, dBc -153 -153 -153 -153 -153 -153 -153 -153						
Input Power per Port at 50°C, 300 300 250 250 200 200   maximum, watts       200						
Mechanical Specifications						
Wind Loading @ Velocity, frontal 477.0 N @ 150 km/h (107.2 lbf @ 150 km/h)						
Wind Loading @ Velocity, lateral 409.0 N @ 150 km/h (91.9 lbf @ 150 km/h)						
Wind Loading @ Velocity, maximum 1,010.0 N @ 150 km/h (227.1 lbf @ 150 km/h)						
Wind Loading @ Velocity, rear 506.0 N @ 150 km/h (113.8 lbf @ 150 km/h)	506.0 N @ 150 km/h (113.8 lbf @ 150 km/h)					
Wind Speed, maximum241 km/h (150 mph)						
Packaging and Weights						
Width, packed 460 mm   18.11 in	460 mm   18.11 in					
Depth, packed 350 mm   13.78 in	350 mm   13.78 in					
Length, packed 2830 mm   111.417 in						
Weight, gross 46.3 kg   102.074 lb	46.3 kg   102.074 lb					
Regulatory Compliance/Certifications						
Agency Classification						
ISO 9001:2015 Designed, manufactured and/or distributed under this quality management system	Designed, manufactured and/or distributed under this quality management system					
Included Products						
BSAMNT-3-Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.						
* Footnotes						
FOULIDLES						

Page 4 of 4

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: September 9, 2024

COMMSCOPE®